

# GEO 14AS

Single line alphanumeric pager



## features

- Large 14 Character Scrolling Display
- Frequency Programmable
- VHF & UHF Versions

## Clear and simple

The frequency programmable pager with a large one-line text display. If the message is longer than 14 characters, an auto scroll feature can be used. The scroll speed can be set by the user.

# GEO 14AS

Single line  
alphanumeric pager

## Specification

<b>Display:</b>	Side read, 14 character, backlit with icons
<b>Addresses:</b>	4 addresses (selectable)
<b>Messages:</b>	16 messages max., 840 characters max, message length 120 char. max
<b>Size:</b>	68 (L) x 46 (W) x 21 (D) mm w/o holster
<b>Weight:</b>	46g (without battery)
<b>Frequency ranges:</b>	VHF 151-159 MHz, UHF 446-454, 454-462, 462-470 MHz
<b>Signalling protocol:</b>	POCSAG
<b>Data transmit rate:</b>	512 or 1200 baud
<b>Sensitivity:</b>	5 $\mu$ V/m @ 512 baud, 7 $\mu$ V/m @ 1200 baud
<b>Beeper output:</b>	Better than 75 db @ 10cm
<b>Power:</b>	Single AAA (LR03) battery



## Main features

- **Scrolling Display:** If the message is longer than 14 characters, an auto scroll feature can be used to read the remaining message. The scroll speed can be set by the user.
- **Synthesized:** The operating frequency can be programmed within the specified range.
- **Urgent Call:** Distinct tone + vibrate mode ideal for emergency services (Fire, Police, Hospitals). Can be pre-programmed to respond to a specific address and call type.
- **Hand Programmable:** The pager addresses and operating frequency can be altered using the buttons on the pager. These features can be individually enabled or inhibited when the pager is first programmed.
- **Selectable Functions:** Both the Repeat Message and Reminder Alert functions can be enabled or inhibited when the pager is first programmed.
- **Multiple Alert Modes:** Tone (4 beep styles)  
Melody  
Vibrate  
"Urgent" Tone + Vibrate

## Other features

- All or Single Message Delete
- Real Time Clock
- Alarm Clock Function
- Unread Message Indicator & reminder
- Repeat Message Indicator
- Low Battery Reminder
- In/Out of Range Indicator
- Selectable Backlight



Scope Communications UK Ltd  
Quantum House  
Steamer Quay  
Totnes, Devon, TQ9 5AL  
England

Tel: +44 (0)1803 860700  
Fax: +44 (0)1803 863716  
Website: [www.scope-uk.com](http://www.scope-uk.com)  
Email: [sales@scope-uk.com](mailto:sales@scope-uk.com)

© Scope Communications Uk Ltd.  
All specifications subject to change without notice. E & OE.